

7. Electric Parts List

7-1. CW28C7VH2X/XEO

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN(OPT)				C612	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
* AA94-00450AASSY-PCB,MAIN(OPT);CW28C7VH,S53A,EUROPE,				C615	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C101	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C616	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C701	2202-000216	C-CERAMIC,MLC-AXIAL:27pF,5%,50V,SL,TP,3.	
C104	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5		C702	2202-000216	C-CERAMIC,MLC-AXIAL:27pF,5%,50V,SL,TP,3.	
C105	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C703	2202-000216	C-CERAMIC,MLC-AXIAL:27pF,5%,50V,SL,TP,3.	
C106	2201-000292	C-CERAMIC,DISC;1nF,10%,50V,Y5P,TP,5x3,5		C704	2202-000216	C-CERAMIC,MLC-AXIAL:27pF,5%,50V,SL,TP,3.	
C107	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm		C705	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm	
C108	2401-000667	C-AL:2.2uF,20%,50V,WT,TP,5x11,5		C706	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm	
C109	2401-002300	C-AL:47uF,20%,50V,GP,TP,6.3x11,5		C707	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm	
C110	2201-000179	C-CERAMIC,DISC;10nF,10%,50V,Y5V,TP,6.5x3		C708	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm	
C111	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm		C709	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C112	2401-000947	C-AL:22uF,20%,35V,GP,TP,5x11,5		C710	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C113	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5		C711	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm	
C114	2201-000982	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,TP,6		C712	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm	
C115	2201-000982	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,TP,6		C713	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm	
C116	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5		C714	2201-000376	C-CERAMIC,DISC;220pF,5%,50V,SL,TP,4x4,5	
C117	2201-000982	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,TP,6		C715	2201-000376	C-CERAMIC,DISC;220pF,5%,50V,SL,TP,4x4,5	
C119	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		C716	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5	
C120	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		C717	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5	
C121	2401-001571	C-AL:47uF,+20%-0%,50V,GP,TP,8x11.5,5		C718	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C122	2201-000292	C-CERAMIC,DISC;1nF,10%,50V,Y5P,TP,5x3,5		C719	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm	
C123	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C724	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP	
C124	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		C725	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP	
C125	2401-000598	C-AL:1uF,20%,50V,GP,TP,4x7,5		C726	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP	
C201	2201-000558	C-CERAMIC,DISC;470pF,10%,50V,Y5P,TP,5x3,5		C727	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP	
C202	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5		C831	2401-002286	C-AL:470uF,20%,16V,WT,TP,10x12.5,5	
C203	2305-000196	C-FILM,MPEF;150nF,5%,63V,TP,-5mm		C832	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C204	2305-000196	C-FILM,MPEF;150nF,5%,63V,TP,-5mm		C833	2401-003034	C-AL:220uF,20%,16V,WT,TP,8x11.5,5	
C205	2201-000464	C-CERAMIC,DISC;30pF,5%,50V,SL,TP,4x3,5,5		C834	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11.5,5	
C206	2305-000196	C-FILM,MPEF;150nF,5%,63V,TP,-5mm		C835	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C207	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5		C836	2401-002286	C-AL:470uF,20%,16V,WT,TP,10x12.5,5	
C208	2305-000355	C-FILM,MPEF;330nF,5%,63V,TP,-5mm		C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C209	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C838	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C210	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm		C839	2401-003034	C-AL:220uF,20%,16V,WT,TP,8x11.5,5	
C211	2305-000355	C-FILM,MPEF;330nF,5%,63V,TP,-5mm		C840	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
C212	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,5		C841	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C213	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm		C851	2401-002286	C-AL:470uF,20%,16V,WT,TP,10x12.5,5	
C214	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5		C852	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C218	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m		C862	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C219	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m		C863	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5	
C220	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m		C864	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C221	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5		C866	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11.5,5	
C222	2201-000653	C-CERAMIC,DISC;68pF,5%,50V,SL,TP,4.0x3,5		C870	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C223	2201-000265	C-CERAMIC,DISC;180pF,5%,50V,RH,TP,8x3,5		C901	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
C224	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5		C902	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C225	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		C903	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5	
C226	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm		C904	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C227	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm		C905	2201-000487	C-CERAMIC,DISC;33pF,5%,50V,SL,TP,5x3,5m	
C228	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm		C906	2201-000487	C-CERAMIC,DISC;33pF,5%,50V,SL,TP,5x3,5m	
C229	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5		C907	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C230	2201-000375	C-CERAMIC,DISC;220pF,5%,50V,RH,TP,9.5x3.		C908	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5	
C231	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5		C909	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
C232	2201-000375	C-CERAMIC,DISC;220pF,5%,50V,RH,TP,9.5x3.		C910	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C251	2201-000568	C-CERAMIC,DISC;47pF,10%,50V,RH,TP,5x3,5		C911	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5	
C601	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7,5		C912	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C602	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7,5		C913	2401-000934	C-AL:22uF,20%,25V,BP,TP,8x11.5,5	
C603	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7,5		C914	2305-000355	C-FILM,MPEF;330nF,5%,63V,TP,-5mm	
C605	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11.5,5		C915	2201-000234	C-CERAMIC,DISC;150pF,5%,50V,CH,TP,9.5x3,5	
C606	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C916	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
C607	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C917	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
C608	2401-002300	C-AL:47uF,20%,50V,GP,TP,6.3x11,5		C918	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
C609	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5		C919	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C610	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5		C920	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5	
C611	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5		C921	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
				C922	2305-000355	C-FILM,MPEF;330nF,5%,63V,TP,-5mm	
				C925	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C926	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5		L201	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C927	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,		L202	2701-000208	INDUCTOR-AXIAL:6.8uH,10%,2.5x3.4mm	
C932	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0		L203	2701-000208	INDUCTOR-AXIAL:6.8uH,10%,2.5x3.4mm	
C934	2201-000472	C-CERAMIC,DISC:330pF,5%,50V,SL,TP,8x3.5,		L204	2701-000149	INDUCTOR-AXIAL:2.7uH,10%,2.5x3.4MM	
CLAMP-	AA65-30018A	CLAMP-WIRE:NYLON-66,-,-,DATL-600,DONG-A,		L205	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CLAMP-	AA65-30109A	CLAMP-FBT:NYLON-66,V2,BLK,-,-,-		L206	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CN501A	3711-003641	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG		L208	2701-001043	INDUCTOR-AXIAL:10uH,10%,14x4.5mA	
CN601A	3711-000961	CONNECTOR-HEADER:BOX,4P,1R,2.5mm,STRAIGH		L601	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CN701	3722-000195	JACK-SCART:42P,-,SN,BLK,NO		L602	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CN702A	3711-003641	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG		L603	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CN803A	3711-000654	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG		L604	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CN804A	3711-000654	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG		L701	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
CN901A	3711-000961	CONNECTOR-HEADER:BOX,4P,1R,2.5mm,STRAIGH		L702	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CN902A	3711-002646	CONNECTOR-HEADER:BOX,7P,1R,2.5mm,STRAIGH		L703	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CN903A	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH		L704	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
COIL/D	AA27-20004K	COIL-DEGAUSSING:-,29,19.0ohm,45T,3000mm,E		L705	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
D-COIL	AA27-20004K	COIL-DEGAUSSING:-,29,19.0ohm,45T,3000mm		L706	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
D103	0401-001024	DIODE-SWITCHING:BAW75,25V,300MA,DO-35,TP		L707	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
D104	0401-001024	DIODE-SWITCHING:BAW75,25V,300MA,DO-35,TP		L708	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
D202	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		L709	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
D203	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		L901	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
D601	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		L902	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
D602	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		L903	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
D901	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		L904	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
D902	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		L905	2701-000158	INDUCTOR-AXIAL:22uH,10%,2.5x3.4mm	
D903	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		Q101	0504-000137	TR-DIGITAL:KSR1202,PNP,300mW,10K/10K,TO-	
D904	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		Q102	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T	
D905	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		Q104	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T	
D906	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		Q105	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
D907	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		Q107	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T	
D908	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		Q108	0504-000150	TR-DIGITAL:KSR2010,PNP,300mW,10K,TO-92,T	
DL201	AA29-90003G	FILTER-LC:-,D5121,LP,12MHz,TP		Q201	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
DZ102	1203-000451	IC-VOLTAGE REGULATOR:33,TO-92,3P,-,PLAST		Q202	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ201	0403-000355	DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500		Q203	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ202	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		Q204	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ203	0403-000660	DIODE-ZENER:MTZ22A,22V,20.15-21.2V,500mW		Q601	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T	
DZ204	0403-000660	DIODE-ZENER:MTZ22A,22V,20.15-21.2V,500mW		Q602	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T	
DZ206	0403-000562	DIODE-ZENER:MTZ7.5B,7.5V,7.07-7.45V,500m		Q701	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ701	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		Q702	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ702	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		Q703	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ703	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		Q704	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ704	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		Q705	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ705	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		Q706	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ706	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		Q707	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ901	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m		Q708	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ902	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m		Q709	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ903	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m		Q901	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
F1101	2904-000302	FILTER-SAW AV:38.90MHz,-,ST,13.9dB,PAL-B		Q902	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
F1102	2904-000301	FILTER-SAW AV:38.90MHz,SIP5K,ST,14.5dB,P		Q903	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
F1103	2903-000181	FILTER-CERAMIC:TR,5.5MHz,-,-,-,TP,TPS5.5		Q904	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
F1104	2903-000129	FILTER-CERAMIC:TR,4.5M/4.72MHz,-,-,-,TP,		Q905	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
△ IC101	1204-001276	IC-SOUND PROCESSOR:TDA9810T,DIP,24P,400M		Q906	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
△ IC201	1204-001108	IC-VIDEO PROCESS:TDA4780/V4,DIP,28P,-,PL		Q907	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T	
△ IC601	1201-001026	IC-POWER AMP:7265,ZIP,11P,19.6MIL,DUAL,1	H/SINK	Q908	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
△ IC701	1001-001073	IC-VIDEO SWITCH:TEA6415C,VIDEO SWITCH,DI		Q909	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
△ IC801	1203-000298	IC-POSIFIXED REG.:7809,TO-220,3P,-,PLAS		Q910	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
△ IC802	1203-000203	IC-POSIFIXED REG.:3050,TO-220,5P,-,PLA	H/SINK	Q911	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L,	
△ IC803	1203-000203	IC-POSIFIXED REG.:3050,TO-220,5P,-,PLA	H/SINK	R101	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ IC804	1203-000243	IC-POSIFIXED REG.:7812A,TO-220,3P,-,PLA	H/SINK	R102	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ IC805	1203-000006	IC-POSIFIXED REG.:7808,TO-220,3P,-,PLAS	H/SINK	R105	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ IC901	AA13-00010A	IC-MCU:-,SDA5457-OTP,8BIT,DIP,CS309AH		R106	2001-000313	R-CARBON:11KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ IC902	1103-001043	IC-EEPROM:24C16,2Kx8BIT,DIP,8P,300MIL,10		R107	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ IC903	1203-000515	IC-VOL. DETECTOR:7042,TO-92,3P,177MIL,PL		R109	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
IF-SHI	AA63-40279A	SHIELD-CASE-IF:-,SPT,TO.25,SCT53A,CW764		R110	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
J270	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R111	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
J271	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R113	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L101	AA26-10006G	TRANS-IF:-,7mG,VIF,-,7mm,8pF,77.8MHz,ST		R116	2001-000969	R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L102	2701-000299	INDUCTOR-AXIAL:13uH,10%,2.5x3.4mm		R119	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L103	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		R121	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L104	2701-000101	INDUCTOR-AXIAL:1.2uH,10%,2.5x3.4mm		R122	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L105	2701-000120	INDUCTOR-AXIAL:12uH,10%,2.5X3.4MM		R123	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
L106	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		R124	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
L107	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		R125	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L108	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		R126	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L109	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R128	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L110	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R201	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L113	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		R202	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc. No.	Code No.	Description ; Specification	Remark
R964	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R966	2001-000708	R-CARBON:390HM,5%,1/8W,AA,TP,1.8X3.2MM	
R967	2001-000362	R-CARBON:1500HM,5%,1/8W,AA,TP,1.8X3.2MM	
R971	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R972	2001-000633	R-CARBON:30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R973	2001-000007	R-CARBON:3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R974	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
R975	2001-000568	R-CARBON:270HM,5%,1/8W,AA,TP,1.8X3.2MM	
R976	2001-000568	R-CARBON:270HM,5%,1/8W,AA,TP,1.8X3.2MM	
R980	2001-000005	R-CARBON:3900HM,5%,1/8W,AA,TP,1.8X3.2MM	
TU01	AA40-10006MTUNER-F/S;TECC2949PG29A(S),PAL-B/G,TR,18		
VR101	2103-000672	VR-SEMI:20Kohm,25%,1/5W,TOP	
VR102	2103-000676	VR-SEMI:50Kohm,25%,1/5W,TOP	
X901	2801-000724	CRYSTAL-UNIT:6MHz,50ppm,28-AAM,20pF,40oh	

ASSY-TERMINAL,BOARD

* AA91-80054GASSY-TERMINAL,BOARD;-,-,-,-,PV2,SCART,CS

T/ANT	AA63-40254A	TERMINAL-BOARD,ANT;-,-,HIPS HB,BLK SCT55A,
INLAY/B	AA64-60395B	INLAY-BACK:622A,PV2 SCART,PS,TO.5,BLK,-,-

ASSY-PCB,POWER

* AA95-00155AASSY-PCB,POWER;CW28C7VH,S53A,28,-,EUROPE

C301	2301-000160	C-FILM,PEF:12nF,5%,50V,TP;11.0x6.0x9.0mm
C302	2201-000132	C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4
C304	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12.5mm,5
C305	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5
C306	2305-000285	C-FILM,MPEF:220nF,5%,100V,TP,10.5X5.5X15
C310	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5
C401	2301-000247	C-FILM,PEF:33nF,5%,50V,TP,8.1x4.5x13mm,5
C402	2301-000213	C-FILM,PEF:220nF,5%,250V,TP,21.5x11.7,5
C407	2303-000186	C-FILM,PPF:22nF,5%,400V,BK,19.5x13.5x8,1
C408	2306-000353	C-FILM,MPPF:6.3nF,5%,1.6KV,BK,26.5x8.5x1
C409	2306-000195	C-FILM,MPPF:360nF,5%,400V,TP,26x19x11.5,
C410	2301-000188	C-FILM,PEF:1nF,5%,100V,TP,10.5x12.5x6.5,
C411	2301-001065	C-FILM,MPPF:47nF,5%,630V,TP,19x15.5x7,7,
C412	2306-001017	C-FILM,MPPF:680nF,5%,400V,TP,26x14.5x24MM
C413	2306-000324	C-FILM,MPPF:3.3nF,5%,1.6KV,TP,28.5x13.5x
C414	2401-003114	C-AL:4.7uF,20%,250V,WT,TP,10x16,5
C416	2401-001527	C-AL:47uF,20%,250V,HR,TP,13x25mm,5m
C417	2401-001527	C-AL:47uF,20%,250V,HR,TP,13x25mm,5m
C418	2201-000132	C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4
C419	2306-000273	C-FILM,MPPF:82nF,5%,400V,BK,19x15.5x7,15
C420	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4
C421	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4
C422	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4
C423	2401-001655	C-AL:680uF,20%,25V,GP,TP,10x20,5
C424	2401-002597	C-AL:220uF,20%,35V,GP,TP,10x12.5,5
C425	2305-000470	C-FILM,MPEF:68nF,5%,100V,TP,-,5mm
C427	2306-000326	C-FILM,MPPF:4.7nF,5%,1.6KV,TP,28.5x16x9m
C455	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5
C456	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm
C457	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m
C458	2301-000175	C-FILM,PEF:15nF,5%,50V,TP,7.1x3.5x13mm,5
C459	2401-001655	C-AL:680uF,20%,25V,GP,TP,10x20,5
C460	2202-000127	C-CERAMIC,MLC-AXIAL:10nF,+80-20%,25V,Y5V
C461	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,
C801	2306-000318	C-FILM,MPPF:220nF,20%,275V,TP,-,22.5mm
C802	2306-000318	C-FILM,MPPF:220nF,20%,275V,TP,-,22.5mm
C803	2201-000315	C-CERAMIC,DISC:2.2nF,+80-20%,250VAC,Y5U,
C804	2401-002289	C-AL:470uF,20%,35V,WT,TP,10x20,5
C805	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5
C806	2306-000323	C-FILM,MPPF:2.2nF,5%,1.6KV,TP,28.5x15.5x
C807	2306-000112	C-FILM,MPPF:100nF,20%,275V,BK,-,15mm
C809	2401-002292	C-AL:47uF,20%,25V,WT,TP,8X11,5
C810	2401-000611	C-AL:1uF,20%,50V,WT,TP,5x11,5
C811	2201-000315	C-CERAMIC,DISC:2.2nF,+80-20%,250VAC,Y5U,
C812	2201-000332	C-CERAMIC,DISC:2.2nF,20%,250VAC,Y5U,TP,1
C813	2401-003066	C-AL:10uF,20%,450V,GP,TP,13x20mm,5m
C814	2401-003190	C-AL:470uF,20%,450V,GPBK,35x45,22.

Loc. No.	Code No.	Description ; Specification	Remark
C816	2401-002262	C-AL:10uF,20%,160V,WT,TP,10x20,5	
C817	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,5	
C818	2201-000551	C-CERAMIC,DISC:470pF,10%,1KV,Y5P,TP,8x5,	
C819	2401-002287	C-AL:470uF,20%,200V,WT,BK,25x40,10	
C820	2401-003024	C-AL:220uF,20%,200V,WT,TP,22x35,10	
C821	2201-000551	C-CERAMIC,DISC:470pF,10%,1KV,Y5P,TP,8x5,	
C822	2401-000737	C-AL:2200uF,20%,50V,GP,TP,18x35.5,7,5	
C823	2201-000551	C-CERAMIC,DISC:470pF,10%,1KV,Y5P,TP,8x5,	
C824	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4	
C825	2401-000722	C-AL:2200uF,20%,25V,WT,TP,16x25,7,5	
C826	2401-000722	C-AL:2200uF,20%,25V,WT,TP,16x25,7,5	
C827	2401-002262	C-AL:10uF,20%,160V,WT,TP,10x20,5	
C828	2401-000722	C-AL:2200uF,20%,25V,WT,TP,16x25,7,5	
C829	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5	
C830	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11.5,5	
C833	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,-,5mm	
C835	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4	
C836	2201-000551	C-CERAMIC,DISC:470pF,10%,1KV,Y5P,TP,8x5,	
C838	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12.5,5	
C839	2201-000551	C-CERAMIC,DISC:470pF,10%,1KV,Y5P,TP,8x5,	
C840	2401-001513	C-AL:47uF,20%,16V,WT,TP,5x11,5	
C842	2401-002211	C-AL:1000uF,20%,35V,LZ,TP,13x25mm,5	
C843	2401-002289	C-AL:470uF,20%,35V,WT,TP,10x20,5	
C844	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
C845	2201-000539	C-CERAMIC,DISC:4.7nF,20%,250V,Y5V,BK,16x	
C846	2201-000539	C-CERAMIC,DISC:4.7nF,20%,250V,Y5V,BK,16x	
CLAMP-	AA65-30109A	CLAMP-FBT:NYLON-66,V2,BLK,-,-,-	
CN801	3711-002641	CONNECTOR-HEADER:BOX,10P,1R,2.54mm,STRAI	
CN803	3710-001141	CONNECTOR-SOCKET:12P,1R,2.5mm,STRAIGHT,S	
CN804	3710-001141	CONNECTOR-SOCKET:12P,1R,2.5mm,STRAIGHT,S	
D301	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D401	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T	
D402	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T	
D403	0401-001024	DIODE-SWITCHING:BAW75,25V,300MA,DO-35,TP	
D404	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
D405	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
D407	0402-001012	DIODE-RECTIFIER:FMP-3FU,1500V,5A,TO-3PF	H/SINK
D410	0402-000537	DIODE-RECTIFIER:RH1A,600V,0.6A,DO-204AC	
D411	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D414	0402-000540	DIODE-RECTIFIER:RU20A,600V,1.5A,-,TP	
D415	0402-000534	DIODE-RECTIFIER:RG10V,400V,1.2A,DO-201,T	
D801	0402-000532	DIODE-RECTIFIER:ERC13-08,800V,1.2A,DO-20	
D802	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T	
D803	0406-001007	DIODE-TVS:P6KE180A,171/180/189V,600W,CAS	
D804	0402-000243	DIODE-RECTIFIER:RC2-V1,2000V,0.2A,DO-201	
D805	0402-000532	DIODE-RECTIFIER:ERC13-08,800V,1.2A,DO-20	
D806	0402-000549	DIODE-BRIDGE:RBV606,600V,6A,-,BK	H/SINK
D807	0402-000213	DIODE-RECTIFIER:ERB12-06,600V,1.0A,DO-41	
D808	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
D810	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D811	0403-000704	DIODE-ZENER:TZP7.5B,7.5V,7.5-8.4V,1W,DO-	
D812	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D813	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D814A	1405-001036	VARISTOR:430V,2500A,14x8.5mm,TP	
D814B	1405-001036	VARISTOR:430V,2500A,14x8.5mm,TP	
D816	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D817	0402-000231	DIODE-RECTIFIER:FMG-G26S,600V,4A,TO-220F	H/SINK
D818	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK
D819	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
D821	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D823	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK
D824	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
D825	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
D826	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D828	0402-000532	DIODE-RECTIFIER:ERC13-08,800V,1.2A,DO-20	
D829	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D830	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
D832	0402-000534	DIODE-RECTIFIER:RG10V,400V,1.2A,DO-201,T	
DZ301	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500m	
DZ302	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500m	
DZ303	0403-000494	DIODE-ZENER:MTZ39,39V,35.36-37.2V,500mW	
DZ304	0403-000700	DIODE-ZENER:TZP33A,33V,31-35V,1W,DO-41,T	
DZ305	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m	
DZ306	0403-000666	DIODE-ZENER:MTZ5.1A,5.1V,4.81-5.07V,500m	
DZ401	0403-000300	DIODE-ZENER:MTZ8.2B,8.2V,7.78-8.19V,500m	
DZ801	0403-000662	DIODE-ZENER:MTZ3.0B,3.0V,3.01-3.22V,500m	
DZ802	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
DZ804	0403-000734	DIODE-ZENER:TZP15B,15V,14.7-16.5V,1W,DO-		R421	2001-001106	R-CARBON(S):220KOHM,5%,1/2W,AA,TP,2.4X6.	
DZ822	0403-000699	DIODE-ZENER:TZP27B,27V,27-30.8V,1W,DO-41		R422	2001-001108	R-CARBON(S):22KOHM,5%,1/2W,AA,TP,2.4X6.4	
F805	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R423	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10mm	
F805A	3602-000114	FUSE-HOLDER:-,30mohm		R424	2008-000221	R-FUSIBLE:0.47ohm,10%,1/2W,AA,TP,4.7x11mm	
F805B	3602-000114	FUSE-HOLDER:-,30mohm		R425	2008-000221	R-FUSIBLE:0.47ohm,10%,1/2W,AA,TP,4.7x11mm	
F806	3601-001064	FUSE-FERRULE:125V,4A,FA,GLASS,2.4x7.5mm		R426	2003-000540	R-METAL OXIDE(S):1Kohm,5%,2W,AF,TP,4x12m	
F807	3601-000120	FUSE-FERRULE:125V,2.5A,FA,GLASS,2.4x7.5mm		R427	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
△ IC301	1204-000517	IC-VERTICAL DEF.:LA7845,SIP,7P,-,PLASTIC H/SINK		R429	2004-000698	R-METAL:3.3Kohm,1%,1/4W,AA,TP,2.4x6.4mm	
△ IC403	1204-001178	IC-VIDEO SYSTEM:TDA8145,DIP,8P,300MIL,PL		R430	2004-002016	R-METAL(S):15Kohm,1%,1/2W,AA,TP,2.5x6.5mm	
△ IC801	AA13-20002K	IC-HYBRID:-,STR-S6709 LF953,SIP,9P,SMPS	H/SINK	R431	2004-002016	R-METAL(S):15Kohm,1%,1/2W,AA,TP,2.5x6.5mm	
△ IC803	1203-000640	IC-PWM CONTROLLER:210,DIP,8P,245MIL,PLAS		R434	2004-001376	R-METAL(S):11Kohm,1%,1/2W,AA,TP,2.4x6.4mm	
△ IC805	0604-001038	PHOTO-COUPLER:TR,130-260%,200mW,DIP-4,ST		R435	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ IC806	1203-000274	IC-POS.FIXED REG.:7805,TO-220,3P,-,PLAS		R436	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L302	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R457	2003-000592	R-METAL OXIDE(S):22ohm,5%,2W,AF,TP,4x12mm	
L303	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R801	1404-000178	THERMISTOR-PTC:7ohm,20%,290V,25A,-,BK	
L401	AA27-10002V	COIL-CHOKE:-,6.3MH,K,-,500MA,-,NY632K(50		R803	1404-001045	THERMISTOR-NTC:4.7OHM,15%,2900K,35.0MW,T	
L402	2701-001034	INDUCTOR-AXIAL:22uH,10%,5x14mm		R804	2001-001116	R-CARBON(S):27OHM,5%,1/2W,AA,TP,2.4X6.4MM	
L404	AA27-00021A	COIL-LINEARITY:-,5UH,OWA14X15,-,BK,20%		R805	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
L405	AA27-40001S	COIL-HORIZ.WIDTH:-,110UH,SB-5S8202,6,PIO		R806	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
L407	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5x5,TP,-		R807	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
L408	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5x5,TP,-		R808	2001-001129	R-CARBON(S):330KOHM,5%,1/2W,AA,TP,2.4X6.	
L409	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R809	2001-001129	R-CARBON(S):330KOHM,5%,1/2W,AA,TP,2.4X6.	
L411	AA27-10004F	COIL-CHOKE:-,56uH,K,-,2.5A,BK,-,DR12x15,		R810	2009-001001	R-METAL PLATE:0.12OHM,10%,5W,CL,TP,5X14X	
L801	AA29-30002F	FILTER-LINE NOISE:-,6mH,2.45A,-,-		R811	2001-001117	R-CARBON(S):2KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
L802	AA29-30002F	FILTER-LINE NOISE:-,6mH,2.45A,-,-		R812	2001-001045	R-CARBON(S):1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
L803	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R813	2001-000109	R-CARBON(S):470OHM,5%,1/2W,AA,TP,2.4X6.4	
L805	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R814	2006-001008	R-CEMENT:8.2OHM,5%,5W,CJ,TP,10.5X14X27M	
L806	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5x5,TP,-		R815	2001-001117	R-CARBON(S):2KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
L810	AA27-10002L	COIL-CHOKE:-,24UH,K,-,2A,-,24UH-K,10X10M		R816	2001-001117	R-CARBON(S):2KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
L811	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5x5,TP,-		R817	2003-001090	R-METAL OXIDE(S):10Kohm,5%,2W,AF,TP,4x12	
L812	AA27-10002L	COIL-CHOKE:-,24UH,K,-,2A,-,24UH-K,10X10M		R820	2003-001093	R-METAL OXIDE(S):12Kohm,5%,2W,AF,TP,3.9x	
L813	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R821	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L816	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5x5,TP,-		R822	2008-001002	R-FUSIBLE(S):0.18ohm,5%,2W,AA,TP,3.9x10mm	
L818	AA27-10002L	COIL-CHOKE:-,24UH,K,-,2A,-,24UH-K,10X10M		R830	2001-001087	R-CARBON(S):18OHM,5%,1/2W,AA,TP,2.4X6.4MM	
L820	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R831	2001-001165	R-CARBON(S):56OHM,5%,1/2W,AA,TP,2.4X6.4MM	
L821	AA27-10002L	COIL-CHOKE:-,24UH,K,-,2A,-,24UH-K,10X10M		R832	2001-001122	R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.	
Q400	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R833	2001-001078	R-CARBON(S):15KOHM,5%,1/2W,AA,TP,2.4X6.4	
Q402	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R834	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4	
Q404	0505-001116	FET-SILICON:BUZ73A,N,200V,22A,0.6ohm,40W		R840	2001-001097	R-CARBON(S):2.4KOHM,5%,1/2W,AA,TP,2.4X6.	
Q405	0502-001062	TR-POWER:2SC5331,NPN,180W,TO-3P,ST,10-3	H/SINK	R841	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
Q406	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T		R842	2001-001106	R-CARBON(S):220KOHM,5%,1/2W,AA,TP,2.4X6.	
Q407	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R844	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.	
△ Q801	0503-000153	TR-DARLINGTON:TIP102,NPN,2W,TO-220,TP,10		R845	2001-001112	R-CARBON(S):24KOHM,5%,1/2W,AA,TP,2.4X6.4	
△ Q803	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L,		R846	2002-001012	R-COMPOSITION:8.2Mohm,10%,1/2W,AA,TP,3.7	
△ Q804	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L,		R848	2008-001058	R-FUSIBLE:0.18ohm,5%,1W,AF,TP,3.9x10mm	
△ Q805	AA13-20004HIC	HYBRID:-,SE135N-LF12,TO220-LF12,3,ERR		R849	2001-001143	R-CARBON(S):4.3KOHM,5%,1/2W,AA,TP,2.4X6.	
R301	2001-000052	R-CARBON(S):3.3KOHM,5%,1/2W,AA,TP,2.4X6.		R851	2008-001080	R-FUSIBLE:27OHM,5%,2W,AF,TP,3.9X10MM	
R302	2001-000052	R-CARBON(S):3.3KOHM,5%,1/2W,AA,TP,2.4X6.		R852	2003-000458	R-METAL OXIDE(S):100ohm,5%,2W,AF,TP,4x12	
R305	2001-001048	R-CARBON(S):1.2OHM,5%,1/2W,AA,TP,2.4X6.4		RL801	3501-001040	RELAY-POWER:12VDC,500mW,10A,1FormA,15mS,	
R306	2001-001163	R-CARBON(S):560OHM,5%,1/2W,AA,TP,2.4X6.4		RL802	3501-001053	RELAY-POWER:5VDC,530MW,10A,1FORMA,15MS,5	
R310	2003-000744	R-METAL OXIDE(S):56ohm,5%,2W,AA,TP,4x12m		△ T403	AA26-50001S	TRANS-HORIZ DRIVE:-,6.0mH,44uH,1.5uH,EI2	
R311	2003-000744	R-METAL OXIDE(S):56ohm,5%,2W,AA,TP,4x12m		△ T444	AA26-00007A	TRANS-FLYBACK:-,FCZ-29A014(S),29INCH,130	
R312	2004-004366	R-METAL(S):1.3Kohm,1%,1/2W,AA,TP,2.5x6.5		T801	AA26-20006X	TRANS-SWITCHING:-,160-260V,130/30/24/8/1	
R313	2001-001048	R-CARBON(S):1.2OHM,5%,1/2W,AA,TP,2.4X6.4		T802	AA26-20004M	TRANS-SWITCHING:-,90-260V,KS,EE2118,7.92	
R314	2004-004366	R-METAL(S):1.3Kohm,1%,1/2W,AA,TP,2.5x6.5					
R315	2001-000016	R-CARBON(S):10HM,5%,1/2W,AA,TP,2.4X6.4MM					
R325	2001-001144	R-CARBON(S):4.7KOHM,5%,1/2W,AA,TP,2.4X6.					
R401	2006-000323	R-CEMENT:56ohm,5%,5W,CB,TP,9.5x13.5x26.					
R402	2001-001168	R-CARBON(S):6.8KOHM,5%,1/2W,AA,TP,2.4X6.					
R403	2001-001108	R-CARBON(S):22KOHM,5%,1/2W,AA,TP,2.4X6.4					
R404	2001-001045	R-CARBON(S):1.2KOHM,5%,1/2W,AA,TP,2.4X6.					
R405	2003-000578	R-METAL OXIDE(S):220ohm,5%,2W,AA,TP,4x12					
R406	2001-001122	R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.					
R407	2003-000578	R-METAL OXIDE(S):220ohm,5%,2W,AA,TP,4x12					
R408	2006-000325	R-CEMENT:56ohm,5%,5W,CH,BK,9.5x27x9.5mm					
R409	2003-000538	R-METAL OXIDE(S):1Kohm,5%,2W,AA,TP,4x12m					
R410	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R411	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R412	2004-001399	R-METAL(S):5.1Kohm,1%,1/2W,AA,TP,2.4X6.4					
R413	2001-001159	R-CARBON(S):510OHM,5%,1/2W,AA,TP,2.4X6.4					
R414	2001-001142	R-CARBON(S):3KOHM,5%,1/2W,AA,TP,2.4X6.4MM					
R415	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm					
R416	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R417	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R418	2001-000539	R-CARBON:24KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R419	2008-001019	R-FUSIBLE:0.2OHM,10%,1/2W,AA,TP,2.5X6.5MM					
R420	2001-001155	R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.					

ASSY-PCB,CRT

* AA95-00114A ASSY-PCB,CRT:-,S53A,28,EUROPE,CW28C7VH

C501	2201-002031	C-CERAMIC,DISC:5pF,0.25pF,50V,NPO,TP,5x3
C502	2201-000436	C-CERAMIC,DISC:2pF,0.3pF,50V,SL,TP,5x3.5
C504	2301-000016	C-FILM,PEF:22nF,5%,100V,TP,7.2x4.5x9.0mm
C505	2301-000016	C-FILM,PEF:22nF,5%,100V,TP,7.2x4.5x9.0mm
C506	2301-000016	C-FILM,PEF:22nF,5%,100V,TP,7.2x4.5x9.0mm
C507	2301-000016	C-FILM,PEF:22nF,5%,100V,TP,7.2x4.5x9.0mm
C509	2301-000016	C-FILM,PEF:22nF,5%,100V,TP,7.2x4.5x9.0mm
C510	2305-000308	C-FILM,MPEF:22nF,5%,250V,-,14.5x6.0x9.5mm
C511	2305-000308	C-FILM,MPEF:22nF,5%,250V,-,14.5x6.0x9.5mm
C512	2305-000308	C-FILM,MPEF:22nF,5%,250V,-,14.5x6.0x9.5mm
C513	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4
C514	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4
C515	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4
C520	2401-000689	C-AL:2200uF,20%,16V,GP,TP,13x25.5
C522	2201-000969	C-CERAMIC,DISC:10nF,+80-20%,3KV,Y5V,TP,-
C531	2401-000636	C-AL:2.2uF,20%,315V,GP,TP,8x12mm,5m

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C532	2401-001527	C-AL:47uF,20%,250V,HR,TP,13x25mm,5m		R518	2001-001095	R-CARBON(S):2.2MOHM,5%,1/2W,AA,TP,2.4X6.	
C535	2401-000914	C-AL:22uF,20%,16V,GP,TP,5x11,5		R525	2002-001006	R-COMPOSITION:4.7KOHM,10%,1/2W,AA,TP,3.7	
C540	2201-000930	C-CERAMIC,DISC:220pF,10%,500V,Y5F,TP,6x4		R528	2008-000292	R-FUSIBLE(S):3.3ohm,5%,2W,AF,TP,3.9x10mm	
CF01	2201-000234	C-CERAMIC,DISC:150pF,5%,50V,CH,TP,9.5x3,		R530	2001-000356	R-CARBON:150KOHM,5%,1/8W,AA,TP,1.8X3.2M	
CF02	2201-000376	C-CERAMIC,DISC:220pF,5%,50V,SL,TP,4x4,5		R531	2001-001086	R-CARBON(S):18KOHM,5%,1/2W,AA,TP,2.4X6.4	
CF03	2201-000653	C-CERAMIC,DISC:68pF,5%,50V,SL,TP,4.0X3.5		R556	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CF04	2201-000516	C-CERAMIC,DISC:4.7nF,+100-0%,500V,Y5U,TP		R557	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CF05	2301-000261	C-FILM,PEF:4.7nF,5%,100V,TP,10.5x12.5x6.		R558	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CF06	2305-000704	C-FILM,MPEF:100nF,5%,250V,TP,16.5x10.3x5		RF01	2001-000347	R-CARBON:13KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CF08	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		RF02	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2M	
CF71	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5		RF03	2001-000534	R-CARBON:240OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CF73	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5		RF05	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
CF74	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm		RF06	2001-000405	R-CARBON:180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CF76	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm		RF07	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CF77	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5		RF08	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
CF78	2401-001157	C-AL:33uF,20%,160V,GP,TP,12.5x20,5		RF09	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CF79	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		RF10	2001-000674	R-CARBON:360OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CF80	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11,5,5		RF11	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CF81	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		RF12	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CN501	AA39-20032G	LEAD-CONNECTOR-ASSY:-,67096-012,5,12P,50		RF13	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CN501B	3711-003641	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG		RF20	2001-000313	R-CARBON:11KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CN502	AA39-20025E	LEAD-CONNECTOR,ASSY:-,67096-010,S,10P,40		RF21	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
CN502B	3711-002641	CONNECTOR-HEADER:BOX,10P,1R,2.54mm,STRAI		RF22	2004-001989	R-METAL:620ohm,5%,1/8W,AA,TP,1.8x3.2mm	
D501	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		RF23	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
D502	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		RF24	2003-001023	R-METAL OXIDE(S):120ohm,0.05,2W,AF,TP,3.	
D504	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		RF25	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
D509	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,		RF26	2001-001179	R-CARBON(S):68KOHM,5%,1/2W,AA,TP,2.4X6.4	
D510	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,		RF27	2001-001179	R-CARBON(S):68KOHM,5%,1/2W,AA,TP,2.4X6.4	
D511	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,		RF28	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
D512	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,		RF29	2001-001071	R-CARBON(S):12KOHM,5%,1/2W,AA,TP,2.4X6.4	
D513	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,		RF30	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
D514	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,		RF31	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
DF01	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		RF32	2003-000746	R-METAL OXIDE(S):56ohm,5%,2W,AF,TP,4x12m	
DF02	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		RF33	2001-001100	R-CARBON(S):2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
DF05	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		RF34	2001-001100	R-CARBON(S):2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
DF06	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T		RF35	2003-000746	R-METAL OXIDE(S):56ohm,5%,2W,AF,TP,4x12m	
DF07	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,		RF36	2003-002009	R-METAL OXIDE(S):390ohm,5%,2W,AF,TP,3.9x	
DF08	0402-001105	DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,		RF37	2001-000969	R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ501	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		RF38	2001-000989	R-CARBON:820KOHM,5%,1/8W,AA,TP,1.8X3.2M	
DZ502	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		RF39	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ503	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		VA999	3704-000112	SOCKET-CRT:14P,29,1.35,5,SN,DHE-A90-700S	
DZ504	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T					
DZ505	0403-000664	DIODE-ZENER:MTZ3.6A,3.6V,3.455-3.695V,50					
DZ506	0403-000655	DIODE-ZENER:MTZ13A,13V,12.11-12.75V,500m					
FV1	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH					
GT06+0	AA39-20010D	LEAD-CONNECTOR,ASSY:-,YFH800-01,S,1P,400					
GT503+	AA39-20010B	LEAD-CONNECTOR,ASSY:-,YFH800-01,S,1P,500					
GT505+	AA39-20010B	LEAD-CONNECTOR,ASSY:-,YFH800-01,S,1P,500					
△ IC501	1201-001131	IC-VIDEO AMP:6111,SIP,9P,-,SINGLE,-,PLAS	H/SINK	B1	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-	
△ IC502	1201-001131	IC-VIDEO AMP:6111,SIP,9P,-,SINGLE,-,PLAS	H/SINK	B2	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-	
△ IC503	1201-001131	IC-VIDEO AMP:6111,SIP,9P,-,SINGLE,-,PLAS	H/SINK	C1	2203-000683	C-CERAMIC,CHIP:27pF,5%,50V,NPO,TP,2012,-	
△ IC505	AA13-20004U	IC-HYBRID:-,SPK102T,SIP,6P,SPOT KILLER,T		C10	2401-000493	C-AL:10uF,20%,50V,LZ,TP,5x11mm,5mm	
L502	2701-000178	INDUCTOR-AXIAL:33uH,10%,2.8x7mm		C100	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,	
LF02	2702-000160	INDUCTOR-RADIAL:4.7uH,10%,6x6.4mm		C101	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
LF03	2701-000112	INDUCTOR-AXIAL:100uH,10%,2.8x7mm		C102	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
LF04	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		C103	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
QF02	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		C104	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
QF03	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		C105	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5	
QF04	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		C106	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
QF06	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		C109	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
QF07	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L,		C11	2401-000242	C-AL:100uF,20%,10V,GP,TP,5x11,5	
QF08	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		C110	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,	
QF09	0502-000131	TR-POWER:2SA1011-D,PNP,1.2W,TO-220,-,60	H/SINK	C111	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
QF10	0502-000153	TR-POWER:2SC2344-D,NPN,1.2W,TO-220,-,60	H/SINK	C112	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R501	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		C113	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R502	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		C119	2203-000784	C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,	
R503	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		C12	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R504	2001-001097	R-CARBON(S):2.4KOHM,5%,1/2W,AA,TP,2.4X6.		C120	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,	
R505	2001-001097	R-CARBON(S):2.4KOHM,5%,1/2W,AA,TP,2.4X6.		C121	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,	
R506	2001-001097	R-CARBON(S):2.4KOHM,5%,1/2W,AA,TP,2.4X6.		C122	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,	
R507	2001-001159	R-CARBON(S):510OHM,5%,1/2W,AA,TP,2.4X6.4		C123	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,	
R510	2001-001194	R-CARBON(S):82KOHM,5%,1/2W,AA,TP,2.4X6.4		C124	2203-000938	C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,	
R511	2001-001194	R-CARBON(S):82KOHM,5%,1/2W,AA,TP,2.4X6.4		C125	2203-000142	C-CERAMIC,CHIP:1.5nF,10%,50V,X7R,TP,2012	
R512	2001-001194	R-CARBON(S):82KOHM,5%,1/2W,AA,TP,2.4X6.4		C126	2203-000938	C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,	
R513	2002-001017	R-COMPOSITION:1K,10%,1/2W,AA,TP,3.7x9.0m		C13	2401-000242	C-AL:100uF,20%,10V,GP,TP,5x11,5	
R514	2002-001017	R-COMPOSITION:1K,10%,1/2W,AA,TP,3.7x9.0m		C14	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R515	2002-001017	R-COMPOSITION:1K,10%,1/2W,AA,TP,3.7x9.0m		C15	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	

ASSY-PCB,F-BOX

* AA95-00154A ASSY-PCB,F-BOX:-,CW28C7VH,S53A,-,-,EUROP

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C16	2401-000242	C-AL:100uF,20%,10V,GP,TP5x11,5		C94	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
C18	2203-000661	C-CERAMIC,CHIP:270pF,5%,50V,NPO,TP,2012,-		C95	2401-000242	C-AL:100uF,20%,10V,GP,TP5x11,5	
C19	2203-000595	C-CERAMIC,CHIP:220pF,5%,50V,NPO,TP,2012,-		C96	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
C2	2203-000683	C-CERAMIC,CHIP:27pF,5%,50V,NPO,TP,2012,-		C97	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
C20	2203-000938	C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,-		C98	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
C21	2401-000027	C-AL:4.7uF,20%,50V,GP,TP5x11,5		C99	2203-000142	C-CERAMIC,CHIP:1.5nF,10%,50V,X7R,TP,2012	
C22	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,		CN203A	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG	
C23	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,		CN205A	3711-003543	CONNECTOR-HEADER:NOWALL,16P,1R,2.54MM,AN	
C24	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		CN206A	3711-002708	CONNECTOR-HEADER:NOWALL,10P,1R,2.5mm,ANG	
C25	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		D1	0403-000666	DIODE-ZENER:MTZ5.1A,5.1V,4.81-5.07V,500m	
C26	2401-001496	C-AL:47uF,20%,16V,GP,TP5x7,5		D2	0401-000005	DIODE-SWITCHING:1N4148,75V,200MA,DO-35,T	
C27	2401-000493	C-AL:10uF,20%,50V,LZ,TP5x11mm,5mm		D3	0403-000666	DIODE-ZENER:MTZ5.1A,5.1V,4.81-5.07V,500m	
C28	2203-000979	C-CERAMIC,CHIP:47nF,10%,50V,X7R,TP,2012,-		D4	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C29	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		D5	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C3	2203-000683	C-CERAMIC,CHIP:27pF,5%,50V,NPO,TP,2012,-		D6	0401-000133	DIODE-SWITCHING:RLS4148,100V,200mA,SOD-8	
C30	2203-001172	C-CERAMIC,CHIP:6pF,0.25pF,50V,NPO,TP,201		D7	0403-000666	DIODE-ZENER:MTZ5.1A,5.1V,4.81-5.07V,500m	
C31	2203-001172	C-CERAMIC,CHIP:6pF,0.25pF,50V,NPO,TP,201		△ IC1	1205-001172	IC-INTERFACE:CIP3250A,PLCC,68P,24MIL,P	
C32	2203-000938	C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,-		△ IC2	1204-001362	IC-VIDEO PROCESS:VPC3215C,PLCC,43P,-,PLA	
C34	2203-000595	C-CERAMIC,CHIP:220pF,5%,50V,NPO,TP,2012,-		△ IC3	1204-001189	IC-HOR./VER.PROCESS:SDA9362,QFP,44P,-,P	
C35	2203-000661	C-CERAMIC,CHIP:270pF,5%,50V,NPO,TP,2012,-		△ IC4	1204-001315	IC-NOISE CANCELLER:SDA9254,QFP,64P,-,C-M	
C36	2203-000938	C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,-		△ IC5	1205-001308	IC-CONTROLLER:SDA9220-5,PLCC,44P,-,PLAST	
C4	2203-000683	C-CERAMIC,CHIP:27pF,5%,50V,NPO,TP,2012,-		△ IC6	1002-001045	IC-D/A CONVERTER:9280,8BIT,PLCC,68P,-,-,	
C40	2401-000242	C-AL:100uF,20%,10V,GP,TP5x11,5		△ IC7	1203-000346	IC-VOL. SUPERVISORY:7705,SOP,8P,150MIL,P	
C41	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		L1	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
C42	2401-000242	C-AL:100uF,20%,10V,GP,TP5x11,5		L10	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C43	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		L12	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C44	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		L13	2701-000146	INDUCTOR-AXIAL:2.2uH,10%,2.5x3.4mm	
C47	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		L15	2701-000146	INDUCTOR-AXIAL:2.2uH,10%,2.5x3.4mm	
C48	2401-000242	C-AL:100uF,20%,10V,GP,TP5x11,5		L16	2701-000146	INDUCTOR-AXIAL:2.2uH,10%,2.5x3.4mm	
C49	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		L17	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C5	2203-002392	C-CERAMIC,CHIP:220nF,+80-20%,50V,Y5V,TP,		L18	2701-000141	INDUCTOR-AXIAL:1mH,5%,2.8x7mm	
C50	2203-000142	C-CERAMIC,CHIP:1.5nF,10%,50V,X7R,TP,2012		L19	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C51	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,-		L2	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
C52	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		L23	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C53	2203-000683	C-CERAMIC,CHIP:27pF,5%,50V,NPO,TP,2012,-		L25	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C54	2203-000683	C-CERAMIC,CHIP:27pF,5%,50V,NPO,TP,2012,-		L26	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C56	2203-000938	C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,-		L27	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C57	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		L3	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
C59	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		L4	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
C6	2203-002392	C-CERAMIC,CHIP:220nF,+80-20%,50V,Y5V,TP,		L5	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C60	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		L6	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C61	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		L7	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C62	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		L8	2701-000146	INDUCTOR-AXIAL:2.2uH,10%,2.5x3.4mm	
C63	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		L9	2701-000146	INDUCTOR-AXIAL:2.2uH,10%,2.5x3.4mm	
C64	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		NR02	2007-000029	R-CHIP:00HM,5%,1/10W,DA,TP,2012	
C65	2401-000242	C-AL:100uF,20%,10V,GP,TP5x11,5		NR3	2007-000029	R-CHIP:00HM,5%,1/10W,DA,TP,2012	
C66	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		Q1	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C67	2401-000242	C-AL:100uF,20%,10V,GP,TP5x11,5		Q4	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
C68	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R111	2007-000401	R-CHIP:1500HM,5%,1/10W,DA,TP,2012	
C69	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R112	2007-000401	R-CHIP:1500HM,5%,1/10W,DA,TP,2012	
C7	2203-002392	C-CERAMIC,CHIP:220nF,+80-20%,50V,Y5V,TP,		R113	2007-000401	R-CHIP:1500HM,5%,1/10W,DA,TP,2012	
C70	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R114	2007-000401	R-CHIP:1500HM,5%,1/10W,DA,TP,2012	
C71	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R115	2007-000267	R-CHIP:1.8KOHM,5%,1/10W,DA,TP,2012	
C72	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R116	2007-000380	R-CHIP:13KOHM,5%,1/10W,DA,TP,2012	
C73	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R117	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
C74	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R119	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
C75	2203-000142	C-CERAMIC,CHIP:1.5nF,10%,50V,X7R,TP,2012		R120	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012	
C76	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,-		R121	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012	
C77	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R122	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012	
C78	2401-000242	C-AL:100uF,20%,10V,GP,TP5x11,5		R123	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012	
C79	2203-000429	C-CERAMIC,CHIP:18pF,5%,50V,NPO,TP,2012,-		R124	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012	
C8	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R13	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C80	2203-000429	C-CERAMIC,CHIP:18pF,5%,50V,NPO,TP,2012,-		R131	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012	
C81	2401-000242	C-AL:100uF,20%,10V,GP,TP5x11,5		R132	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012	
C82	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R14	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C83	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R15	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C84	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R16	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C85	2401-000242	C-AL:100uF,20%,10V,GP,TP5x11,5		R17	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C86	2203-000555	C-CERAMIC,CHIP:20pF,5%,50V,NPO,TP,2012,-		R18	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C87	2203-000555	C-CERAMIC,CHIP:20pF,5%,50V,NPO,TP,2012,-		R19	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C88	2203-000555	C-CERAMIC,CHIP:20pF,5%,50V,NPO,TP,2012,-		R20	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C89	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R21	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C9	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R22	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C90	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R23	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C91	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R24	2007-001133	R-CHIP:680HM,5%,1/10W,DA,TP,2012	
C92	2401-000242	C-AL:100uF,20%,10V,GP,TP5x11,5		R25	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012	
C93	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R26	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R43	2007-000947	R-CHIP:470HM,5%,1/10W,DA,TP,2012		C611	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
R45	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012		C612	2203-000716	C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012	
R46	2007-000781	R-CHIP:330HM,5%,1/10W,DA,TP,2012		C613	2203-000716	C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012	
R47	2007-000409	R-CHIP:15KOHM,5%,1/10W,DA,TP,2012		C614	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm	
R48	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012		C615	2203-000595	C-CERAMIC,CHIP:220pF,5%,50V,NPO,TP,2012,	
R49	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012		C616	2203-000938	C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,	
R50	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012		C617	2203-000142	C-CERAMIC,CHIP:1.5nF,10%,50V,X7R,TP,2012	
R51	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012		C618	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
R52	2007-000781	R-CHIP:330HM,5%,1/10W,DA,TP,2012		C619	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
R53	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012		C622	2203-000701	C-CERAMIC,CHIP:2pF,0.25pF,50V,NPO,TP,201	
R55	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012		C623	2203-000701	C-CERAMIC,CHIP:2pF,0.25pF,50V,NPO,TP,201	
R60	2007-000572	R-CHIP:220OHM,5%,1/10W,DA,TP,2012		C624	2203-001077	C-CERAMIC,CHIP:56pF,5%,50V,NPO,TP,2012,-	
R61	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012		C625	2203-001077	C-CERAMIC,CHIP:56pF,5%,50V,NPO,TP,2012,-	
R62	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012		C626	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm	
R63	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012		C627	2203-000938	C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,	
R65	2001-000016	R-CARBON(S):10HM,5%,1/2W,AA,TP,2.4X6.4MM		C628	2203-000142	C-CERAMIC,CHIP:1.5nF,10%,50V,X7R,TP,2012	
R66	2007-000267	R-CHIP:1.8KOHM,5%,1/10W,DA,TP,2012		C629	2203-001077	C-CERAMIC,CHIP:56pF,5%,50V,NPO,TP,2012,-	
R67	2007-000518	R-CHIP:2.7KOHM,5%,1/10W,DA,TP,2012		C630	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm	
R68	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012		C631	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R69	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012		C632	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,	
R70	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012		C633	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,	
R71	2007-000001	R-CHIP:68KOHM,5%,1/10W,DA,TP,2012		C634	2203-000784	C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,	
R72	2007-000355	R-CHIP:12KOHM,5%,1/10W,DA,TP,2012		C635	2203-000784	C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,	
R73	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012		C636	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R74	2007-000981	R-CHIP:5.6KOHM,5%,1/10W,DA,TP,2012		C637	2401-001026	C-AL:3.3UF,20%,50V,GP,TP,5X11,5	
R75	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012		C638	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm	
R76	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012		C639	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm	
R77	2007-000947	R-CHIP:470HM,5%,1/10W,DA,TP,2012		C640	2203-000938	C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,	
R78	2007-000947	R-CHIP:470HM,5%,1/10W,DA,TP,2012		C641	2203-000142	C-CERAMIC,CHIP:1.5nF,10%,50V,X7R,TP,2012	
R79	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012		C642	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm	
R80	2007-000822	R-CHIP:390OHM,5%,1/10W,DA,TP,2012		C643	2401-000914	C-AL:22uF,20%,16V,GP,TP,5x11,5	
R81	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012		C644	2401-000914	C-AL:22uF,20%,16V,GP,TP,5x11,5	
R82	2007-000267	R-CHIP:1.8KOHM,5%,1/10W,DA,TP,2012		C645	2401-000914	C-AL:22uF,20%,16V,GP,TP,5x11,5	
R83	2007-000401	R-CHIP:150OHM,5%,1/10W,DA,TP,2012		C646	2401-000914	C-AL:22uF,20%,16V,GP,TP,5x11,5	
R84	2007-001133	R-CHIP:68OHM,5%,1/10W,DA,TP,2012		C650	2203-000979	C-CERAMIC,CHIP:47nF,10%,50V,X7R,TP,2012,	
R85	2007-000781	R-CHIP:330HM,5%,1/10W,DA,TP,2012		C653	2203-000784	C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,	
R86	2007-000781	R-CHIP:330HM,5%,1/10W,DA,TP,2012		C654	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,	
R87	2007-000781	R-CHIP:330HM,5%,1/10W,DA,TP,2012		C655	2203-000784	C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,	
R88	2007-000781	R-CHIP:330HM,5%,1/10W,DA,TP,2012		C656	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,	
R89	2007-001133	R-CHIP:68OHM,5%,1/10W,DA,TP,2012		C657	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,	
R90	2007-000781	R-CHIP:330HM,5%,1/10W,DA,TP,2012		C658	2203-000784	C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,	
R91	2007-000781	R-CHIP:330HM,5%,1/10W,DA,TP,2012		C661	2203-000784	C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,	
R92	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012		C662	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,	
R93	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012		C663	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,	
R94	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012		C664	2203-000784	C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,	
X1	2801-003432	CRYSTAL-UNIT:20.25MHz,30ppm,28-AAA,13pF,		C665	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-	
X2	2801-003433	CRYSTAL-UNIT:12MHz,30ppm,28-AAA,30pF,30o		C666	2203-000716	C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012	
X3	2801-003572	CRYSTAL-UNIT:6.75MHz,30ppm,28-AAA,20pF,1		C667	2401-000493	C-AL:10uF,20%,50V,LZ,TP,5x11mm,5mm	
				C684	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				C694	2401-002212	C-AL:10uF,20%,25V,WT,TP,5x11,5,0mm	
				C695	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,	
				C696	2203-000716	C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012	
				C697	2203-000716	C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012	
				CN601A	3711-002710	CONNECTOR-HEADER:NOWALL,15P,1R,2.5mm,ANG	
				CN602A	3711-002710	CONNECTOR-HEADER:NOWALL,15P,1R,2.5mm,ANG	
				CN603	AA61-10068ABRACKET-PCB:-,M2160,SPT,TO,3,-,-,-		
				CN604	AA61-10068ABRACKET-PCB:-,M2160,SPT,TO,3,-,-,-		
				D601	0401-000133	DIODE-SWITCHING:RLS4148,100V,200mA,SOD-8	
				D602	0401-000133	DIODE-SWITCHING:RLS4148,100V,200mA,SOD-8	
				DZ601	0403-000546	DIODE-ZENER:MTZ3.6B,3.6V,3.6-3.845V,500m	
				△ IC601	1204-001163	IC-SOUND PROCESSOR:MSP3410D,PLCC,68P,24.	
				△ IC603	1201-000407	IC-POWER AMP:7050,DIP,8P,-,SINGLE,-,PLAS	
				L601	2701-000170	INDUCTOR-AXIAL:3.9uH,10%,2.8x7mm	
				L602	2701-000170	INDUCTOR-AXIAL:3.9uH,10%,2.8x7mm	
				L603	2701-000112	INDUCTOR-AXIAL:100uH,10%,2.8x7mm	
				R603	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
				R604	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
				R605	2007-000881	R-CHIP:4.7ohm,5%,1/10W,DA,TP,2012	
				R606	2007-000881	R-CHIP:4.7ohm,5%,1/10W,DA,TP,2012	
				R607	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4	
				R608	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
				R609	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
				R610	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
				R611	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
				R612	2007-000686	R-CHIP:3.3KOHM,5%,1/10W,DA,TP,2012	
				R613	2007-000686	R-CHIP:3.3KOHM,5%,1/10W,DA,TP,2012	
				R614	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	

ASSY-PCB,SUB POWER

* AA95-00096AASSY-PCB,SUB POWER:-,28C7,S53A,PAL,-,-

3(2)P
BRACKE
D801
F801
FA801
FA802
H01
R801

AA39-20176ALEAD CONNECTOR-ASSY:-,YFH800-03,S,3(2)P,
AA61-11005ABRACKET-PFC:-,764A,SECC-1,T1,0,-,PFC BOA
1405-000187 VARISTOR:750V,1250A,12.5x7mm,TP
3601-001007 FUSE-FERRULE:250V,6.3A,TL,GLASS,5.2x20mm
3602-000114 FUSE-HOLDER:-,30mohm
3602-000114 FUSE-HOLDER:-,30mohm
AA47-20001A SPARK-GAP:-,1CE60,6.1MM,KS,EU,BK
2002-001010 R-COMPOSITION:1.8Mohm,10%,1/2W,AA,TP,3.7

ASSY-SOUND

* AA95-40011NASSY-SOUND:-,29,SCT53B,-,-,-

C601
C602
C603
C604
C605
C606
C607
C610

2203-000192 C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,
2203-000192 C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,
2401-001840 C-AL:100uF,20%,16V,GP,TP,6.3x11,5
2401-001840 C-AL:100uF,20%,16V,GP,TP,6.3x11,5
2401-000480 C-AL:10uF,20%,50V,GP,TP,5x11,5
2203-000979 C-CERAMIC,CHIP:47nF,10%,50V,X7R,TP,2012,
2401-000603 C-AL:1uF,20%,50V,GP,TP,5x11,5

C611
C612
C613
C614
C615
C616
C617
C618
C619
C622
C623
C624
C625
C626
C627
C628
C629
C630
C631
C632
C633
C634
C635
C636
C637
C638
C639
C640
C641
C642
C643
C644
C645
C646
C650
C653
C654
C655
C656
C657
C658
C661
C662
C663
C664
C665
C666
C667
C684
C694
C695
C696
C697
CN601A
CN602A
CN603
CN604
D601
D602
DZ601
△ IC601
△ IC603
L601
L602
L603
R603
R604
R605
R606
R607
R608
R609
R610
R611
R612
R613
R614

2401-000603 C-AL:1uF,20%,50V,GP,TP,5x11,5
2203-000716 C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012
2203-000716 C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012
2401-002235 C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm
2203-000595 C-CERAMIC,CHIP:220pF,5%,50V,NPO,TP,2012,
2203-000938 C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,
2203-000142 C-CERAMIC,CHIP:1.5nF,10%,50V,X7R,TP,2012
2203-000444 C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-
2203-000444 C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-
2203-000701 C-CERAMIC,CHIP:2pF,0.25pF,50V,NPO,TP,201
2203-000701 C-CERAMIC,CHIP:2pF,0.25pF,50V,NPO,TP,201
2203-001077 C-CERAMIC,CHIP:56pF,5%,50V,NPO,TP,2012,-
2203-001077 C-CERAMIC,CHIP:56pF,5%,50V,NPO,TP,2012,-
2401-002235 C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm
2203-000938 C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,
2203-000142 C-CERAMIC,CHIP:1.5nF,10%,50V,X7R,TP,2012
2401-002235 C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm
2401-002235 C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm
2203-000192 C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,
2203-000753 C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,
2203-000753 C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,
2203-000784 C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,
2203-000784 C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,
2203-000192 C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,
2401-001026 C-AL:3.3UF,20%,50V,GP,TP,5X11,5
2401-002235 C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm
2401-002235 C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm
2203-000938 C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,
2203-000142 C-CERAMIC,CHIP:1.5nF,10%,50V,X7R,TP,2012
2401-002235 C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm
2401-000914 C-AL:22uF,20%,16V,GP,TP,5x11,5
2401-000914 C-AL:22uF,20%,16V,GP,TP,5x11,5
2401-000914 C-AL:22uF,20%,16V,GP,TP,5x11,5
2203-000979 C-CERAMIC,CHIP:47nF,10%,50V,X7R,TP,2012,
2203-000784 C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,
2203-000753 C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,
2203-000784 C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,
2203-000753 C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,
2203-000753 C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,
2203-000784 C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,
2203-000784 C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,
2203-000753 C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,
2203-000753 C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,
2203-000784 C-CERAMIC,CHIP:330pF,5%,50V,NPO,TP,2012,
2203-000716 C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012
2401-000493 C-AL:10uF,20%,50V,LZ,TP,5x11mm,5mm
2401-000480 C-AL:10uF,20%,50V,GP,TP,5x11,5
2401-002212 C-AL:10uF,20%,25V,WT,TP,5x11,5,0mm
2203-000753 C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,
2203-000716 C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012
2203-000716 C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012
3711-002710 CONNECTOR-HEADER:NOWALL,15P,1R,2.5mm,ANG
3711-002710 CONNECTOR-HEADER:NOWALL,15P,1R,2.5mm,ANG
AA61-10068ABRACKET-PCB:-,M2160,SPT,TO,3,-,-,-
AA61-10068ABRACKET-PCB:-,M2160,SPT,TO,3,-,-,-
0401-000133 DIODE-SWITCHING:RLS4148,100V,200mA,SOD-8
0401-000133 DIODE-SWITCHING:RLS4148,100V,200mA,SOD-8
0403-000546 DIODE-ZENER:MTZ3.6B,3.6V,3.6-3.845V,500m
1204-001163 IC-SOUND PROCESSOR:MSP3410D,PLCC,68P,24.
1201-000407 IC-POWER AMP:7050,DIP,8P,-,SINGLE,-,PLAS
2701-000170 INDUCTOR-AXIAL:3.9uH,10%,2.8x7mm
2701-000170 INDUCTOR-AXIAL:3.9uH,10%,2.8x7mm
2701-000112 INDUCTOR-AXIAL:100uH,10%,2.8x7mm
2007-000586 R-CHIP:22KOHM,5%,1/10W,DA,TP,2012
2007-000586 R-CHIP:22KOHM,5%,1/10W,DA,TP,2012
2007-000881 R-CHIP:4.7ohm,5%,1/10W,DA,TP,2012
2007-000881 R-CHIP:4.7ohm,5%,1/10W,DA,TP,2012
2001-000028 R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4
2007-000300 R-CHIP:10KOHM,5%,1/10W,DA,TP,2012
2007-000300 R-CHIP:10KOHM,5%,1/10W,DA,TP,2012
2007-000290 R-CHIP:100OHM,5%,1/10W,DA,TP,2012
2007-000290 R-CHIP:100OHM,5%,1/10W,DA,TP,2012
2007-000686 R-CHIP:3.3KOHM,5%,1/10W,DA,TP,2012
2007-000686 R-CHIP:3.3KOHM,5%,1/10W,DA,TP,2012
2007-000468 R-CHIP:1KOHM,5%,1/1

ASSY-PCB,SUB POWER

* AA95-00096AASSY-PCB,SUB POWER:-,28C7,S53A,PAL,-,-

3(2)P	AA39-20176ALEAD CONNECTOR-ASSY:-,YFH800-03,S,2(2)P,
BRACKE	AA61-11005ABRACKET-PFC:-,764A,SECC-1,T1.0,-,PFC BOA
D801	1405-000187 VARISTOR:750V,1250A,12.5x7mm,TP
F801	3601-001007 FUSE-FERRULE:250V,6.3A,TL,GLASS,5.2x20mm
FA801	3602-000114 FUSE-HOLDER:-,30mohm
FA802	3602-000114 FUSE-HOLDER:-,30mohm
H01	AA47-20001ASPARK-GAP:-,ICE60,6.1MM,KS,EU,BK
R801	2002-001010 R-COMPOSITION:1.8Mohm,10%,1/2W,AA,TP,3.7

ASSY-SOUND

* AA95-40011NASSY-SOUND:-,29,SCT53B,-,-,-

C601	2203-000192 C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,
C602	2203-000192 C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,
C603	2401-001840 C-AL:100uF,20%,16V,GP,TP,6.3x11,5
C604	2401-001840 C-AL:100uF,20%,16V,GP,TP,6.3x11,5
C605	2401-000480 C-AL:10uF,20%,50V,GP,TP,5x11,5
C606	2203-000979 C-CERAMIC,CHIP:47nF,10%,50V,X7R,TP,2012,
C610	2401-000603 C-AL:1uF,20%,50V,GP,TP,5x11,5

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R617	2007-000931	R-CHIP:4700HM,5%,1/10W,DA,TP,2012					
R618	2007-000931	R-CHIP:4700HM,5%,1/10W,DA,TP,2012					
R619	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012					
R620	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012					
R621	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012					
R622	2007-000290	R-CHIP:1000HM,5%,1/10W,DA,TP,2012					
R623	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012					
R632	2007-000931	R-CHIP:4700HM,5%,1/10W,DA,TP,2012					
R633	2007-000931	R-CHIP:4700HM,5%,1/10W,DA,TP,2012					
R634	2007-000931	R-CHIP:4700HM,5%,1/10W,DA,TP,2012					
R635	2007-000931	R-CHIP:4700HM,5%,1/10W,DA,TP,2012					
R636	2007-000931	R-CHIP:4700HM,5%,1/10W,DA,TP,2012					
R660	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012					
R661	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012					
R666	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012					
R671	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012					
X601	2801-000186	CRYSTAL-UNIT:18.432MHZ,25PPM,28-AAAM,8PF,					
REMOCON							
	* AA59-00025	AREMOCON;-;DP,TM57,AA59-00023A,-;-;-;-;-;					
ASSY-POWER,CORD							
	* AA96-00094	AASSY-POWER,CORD:DP,CP2/NO(4.0),H/C350MM,KJP140					
HDR/C	AA61-20050A	HOLDER-CORD;-;-;PP,V0,BLK,DO					
PWR/C	AA39-10003B	POWER-CORD;-;KJP-140,KLCE-2F,2.4m,HOUS,S					
ASSY-CABINET							
	* HA91-100025	ASSY-CABINET,FRONT:28C7,S53A					
BACK	HA64-31364A	CABINET-BACK;-;-;28C7,HIPS,V2,BLK,-;-					
BADGE	AA64-70117B	BADGE-BRAND:AL,SS,SILVER,L65,R2000,-;-					
BOSS	HA61-40010A	BOSS-WING;-;-;HIPS,HB,NTR,-;-					
C/CORD	AA65-30008A	CLAMP-CORD:PE,HB,BLK,-;-;-					
C/DCOIL	AA65-30004A	CLAMP-D.COIL:NYLON-66,V0,NTR,DADH300,25 20					
C/FBT	AA65-30009A	CLAMP-FBT:ABS,V0,BLK,-;-;-					
C/WIRE	AA65-30018A	CLAMP-WIRE:NYLON-66,-;-;DATL-600,DONG-A,-					
CATCH/D	AA61-30001A	CATCH-DOOR;-;-;-;KIFUCO LA701,-					
CB	AA63-60001X	SPACER-FELT:FELT,T0.5,BLK,-;330X15,-;-					
CB+CF	6003-001025	SCREW-TAPPING:RH,M4,L20,BLK					
CB+TER	6003-001025	SCREW-TAPPING:RH,M4,L20,BLK					
CRT+CF	AA60-10051D	SCREW-ASSY:WC,HH,+,M5,30,SWRCH18A,ZPC,-					
DOOR/C	HA64-50258A	DOOR-CONTROL;-;-;28C7,-;HIPS,HB,GRY,-;-					
FELT/S	AA63-60001U	SPACER-FELT:FELT,T0.5,BLK,150X15,-;-					
FRONT	HA64-300070	CABINET-FRONT;-;-;28C7,SV-808P,HB,GRY,100HZ					
GUIDE/L	AA61-50032A	GUIDE-LED:6201,ABS,HB,BLK,-;-;-					
GUMCRT	HA63-600001	SPACER-GUM,CRT;-;NTR RUBBER,T2.4,BLK,-;-					
I/LED	AA64-00191A	INDICATOR-LED;-;-;28C7,-;ACRYL,-;CLR,-					
IND+CF	6003-001026	SCREW-TAPPING:RH,+,2,M4,L15,ZPC(BLK)SWRCH18					
INLAY	AA64-00189B	INLAY-CONTRTOL:28C7,S51A,PS,T0.3,BLK,-;-					
KC+CF	6003-001026	SCREW-TAPPING:RH,+,2,M4,L15,ZPC(BLK)SWRCH18					
KNOB/C	AA64-00217B	KNOB-CONTROL:DP,28W6,AA64-10809C,-;-;GRAY					
KNOB/P	HA64-10808A	KNOB-POWER;-;-;28C7,M/S,ABS,HB,G3673					
PWB	6001-000677	SCREW-MACHINE:RH,+,M3,L6,ZPC(YEL),SM20C,-					
PWB+CF	6003-001023	SCREW-TAPTITE:RWH,+,B,M3,L10,ZPC(YEL)SWRCH1					
SPK+CF	6003-001026	SCREW-TAPPING:RH,+,2,M4,L15,ZPC(BLK)SWRCH18					
SPRING	AA61-60003J	SPRING-CS;-;-;SUS304,0.5,OD6,H12,N7,-;-;-					
TER+SC	6003-001025	SCREW-TAPPING:RH,M4,L20,BLK					
W/RMC	AA64-00190A	WINDOW-RMC;-;-;28C7,-;PC,-;VIOLET,-					
ASSY-SPEAKER							
	* HA96-00092	AASSY-SPEAKER;-;-;16##,6W,3001-001038,AA39-000					
SPK	3001-001038	SPEAKER:6W,16OHM,92DB,140HZ					
LEAD/C	AA39-00005B	LEAD CONNECTOR-ASSY;-;-;YSH250-04,REC,REC,4P,1200,80					
ASSY-ACCESSORY							
	BATTERY	4301-000121 BATTERY-MN:1.5V,-;AAA,10.5x44.5m,HOLDER					
ASSY-CRT							
	* HA94-00744A	AASSY-CRT:A66EAK5552X54,+380MG,28,ITC,C					
△ CRT	AA03-10035E	CRT-COLOR;-;-;A66EAK5552X54,+380mG,28,110d					
LEAD/C	AA39-20519A	LEAD CONNECTOR-ASSY;-;-;YFH806-06,-;-;6(4)P,500MM,1617					
ASSY-PCB,CONTROL							
	* AA95-00174A	AASSY-PCB,CONTROL:DP,S53A,28C7,HUNGARY					
	3(2)P	AA39-20179A	LEAD-CONNECTOR,ASSY;-;-;YFH150-03,S,3(2)P,				
C701	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP					
C702	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP					
C703	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP					
C704	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP					
CN701	AA39-20071A	LEAD-CONNECTOR,ASSY;-;-;YBNH025-12,67096-0					
CN801	AA39-20069A	LEAD-CONNECTOR,ASSY;-;-;YBNH025-05,67096-0					
CNC01	AA39-20052C	LEAD-CONNECTOR,ASSY;-;-;YBNH025-04,YSH025-					
CPS01	2401-002144	C-AL:47uF,20%,16V,GP,TP5x11,5					
DPS01	0601-000198	LED:ROUND,RED/GRN,5.0mm,630/565nm					
G-LED	AA61-50032A	GUIDE-LED:6201,ABS,HB,BLK,-;-;-					
HC01	AA59-60003J	MODULE-REMOCON;-;-;ORC-06H2,38KHZ,940NM,ME					
JA701A	3722-001367	JACK-RCA:1P,3.4MM,AU,YEL,-					
JA701B	3722-001368	JACK-RCA:1P,3.4MM,AU,WHT,-					
JA701C	3722-001369	JACK-RCA:1P,3.4MM,AU,RED,-					
JA702	3722-000544	JACK-VHS:12P,11.5mm,AG,BLK,N					
JA703	3722-001061	JACK-PHONE:1P,3.6mm,AG,BLK,N					
L701	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm					
L702	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm					
L703	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm					
L704	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm					
Q701	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T					
R701	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R702	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RC01	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M					
RC02	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M					
RC03	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RC04	2001-000890	R-CARBON:6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M					
RC05	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RPS01	2001-001114	R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4					
RPS02	2001-001114	R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4					
RPS03	2001-000020	R-CARBON(S):22OHM,5%,1/2W,AA,TP,2.4X6.4M					
RPS04	2001-001108	R-CARBON(S):22KOHM,5%,1/2W,AA,TP,2.4X6.4					
SCREW	6001-000057	SCREW-MACHINE:RH,+,M3,L6,ZPC(BLK),SWRCH1					
SWC01	3404-000176	SWITCH-TACT:12V,50mA,90-150gf,6x6mm,SPST					
SWC02	3404-000176	SWITCH-TACT:12V,50mA,90-150gf,6x6mm,SPST					
SWC03	3404-000176	SWITCH-TACT:12V,50mA,90-150gf,6x6mm,SPST					
SWC04	3404-000176	SWITCH-TACT:12V,50mA,90-150gf,6x6mm,SPST					
SWC05	3404-000176	SWITCH-TACT:12V,50mA,90-150gf,6x6mm,SPST					
SWP01	3403-000179	SWITCH-PUSH:250V,5A,DPST,-;JPW-2104B					